DIGITAL MOTOR CHECKER EMC-38

Electric Motor, Generator and Transformer Trouble Shooter
Know in a few minutes what the problem is: Electrical or Mechanical,
coil or rotor, internal fault or ground fault



Features:

- Insulation Resistance (IR) Measurement
- Identify open and short circuits / loose connections in a winding coil
- Identify interterm shorts.
- Detect rotor bar problems without dismounting the rotor
- Inductance of the winding with respect to different positions for rotor for detecting blow holes or cracks in the rotor bars.
- Simple operation, accurate & quick assessment of motor condition.
- Shock proofed rubber casing
- Low battery Indication

Fast Checks of On-Line Motors:

EMC-38 is a Digital portable diagnostic tool for Electrical Engineer and is used for quick on - site checks of electric motor and other three - phase machines.

A reduction in machine performance, such as inefficient operation or tripping of overloads, may indicate mechanical or electrical faults. If the fault is electrical the EMC-38 will immediately detect it, without having to dismantle the equipment.

The instruments has three separate operating modes to measure different types of faults like fully insulation, open circuits / loose connections, short circuits and rotor defects. Motor insulation is tested with a high voltage of 500V & 1000V DC supplied by the instrument.

Technical Specifications

A) INSULATION RESISTANCE: $0-200~M\Omega$ at 500~V~DC ± (2% + 1digit), $0.1~M\Omega$ resolution $0-2000~M\Omega$ at 1000~V~DC ± (2% + 1digit), $0.1~M\Omega$ resolution

B) RESISTANCE:	RANGE	RESOLUTION
C) INDUCTANCE:	$0 - 200 \text{ milli } \Omega$ $0 - 2 \Omega$ $0 - 20 \Omega$ $0 - 200 \Omega$ $\frac{\text{RANGE}}{0 - 2 \text{ m H}}$ 0 - 200 mH 0 - 2000 mH	$\begin{array}{c} 0.10 \text{ milli } \Omega \\ 0.001 \ \Omega \\ 0.01 \ \Omega \\ 0.10 \ \Omega \\ \hline \textbf{RESOLUTION} \\ 0.001 \ \text{mH} \\ 0.01 \ \text{mH} \\ 0.1 \ \text{mH} \\ 1 \ \text{mH} \end{array}$

^{*} Display:3½ LCD * Temp.Range:0- 55°C * Size:210x125x65 * Weight:1000gms * Power: 6 AA size (Battery Pack with Charger Optional)

MCM INSTRUMENTS

Plot No. 4, Srivaishnavi Homes, Ramakrishna Nagar, Madinaguda, Hyderabad -500049, **Phone:** +91-40-64547744 , **Mobile:** +91 9440845436, +91 9908747296 Email: mcm_instrument@yahoo.co.in , **Website:** www.mcminstruments.com